

RMXdigital Timeslot Map

		FACET 2						FACET 3						FACET 4						FACET 5					
TS	TS_HEX	SIGNAL NAME	FADER	GLOBAL	LOCAL	PAIR	S/D	SIGNAL NAME	FADER	GLOBAL	LOCAL	PAIR	S/D	SIGNAL NAME	FADER	GLOBAL	LOCAL	PAIR	S/D	SIGNAL NAME	FADER	GLOBAL	LOCAL	PAIR	S/D
0	0	DSP0	1	65665	129	1	SD	DSP 2	1	65729	193	17	SD	I/O 1:AUDIO 1L - LOGIC 1	1	65793	257	33	S/D	I/O 3:AUDIO 1L - LOGIC 1	1	65857	321	49	S/D
1	1	DSP0	1	65666	130	1	SD	DSP 2	1	65730	194	17	SD	AUDIO 1R	1	65794	258	33	S/D	AUDIO 1R	1	65858	322	49	S/D
2	2	DSP0	2	65667	131	2	SD	DSP 2	2	65731	195	18	SD	I/O 1:AUDIO 2L - LOGIC 2	2	65795	259	34	S/D	I/O 3:AUDIO 2L - LOGIC 2	2	65859	323	50	S/D
3	3	DSP0	2	65668	132	2	SD	DSP 2	2	65732	196	18	SD	AUDIO 2R	2	65796	260	34	S/D	AUDIO 2R	2	65860	324	50	S/D
4	4	DSP0	3	65669	133	3	SD	DSP 2	3	65733	197	19	SD	I/O 1:AUDIO 3L - LOGIC 3	3	65797	261	35	S/D	I/O 3:AUDIO 3L - LOGIC 3	3	65861	325	51	S/D
5	5	DSP0	3	65670	134	3	SD	DSP 2	3	65734	198	19	SD	AUDIO 3R	3	65798	262	35	S/D	AUDIO 3R	3	65862	326	51	S/D
6	6	DSP0	4	65671	135	4	SD	DSP 2	4	65735	199	20	SD	I/O 1:AUDIO 4L - LOGIC 4	4	65799	263	36	S/D	I/O 3:AUDIO 4L - LOGIC 4	4	65863	327	52	S/D
7	7	DSP0	4	65672	136	4	SD	DSP 2	4	65736	200	20	SD	AUDIO 4R	4	65800	264	36	S/D	AUDIO 4R	4	65864	328	52	S/D
8	8	DSP0	5	65673	137	5	SD	DSP 2	5	65737	201	21	SD	I/O 1:AUDIO 5L - LOGIC 5	5	65801	265	37	S/D	I/O 3:AUDIO 5L - LOGIC 5	5	65865	329	53	S/D
9	9	DSP0	5	65674	138	5	SD	DSP 2	5	65738	202	21	SD	AUDIO 5R	5	65802	266	37	S/D	AUDIO 5R	5	65866	330	53	S/D
10	A	DSP0	6	65675	139	6	SD	DSP 2	6	65739	203	22	SD	I/O 1:AUDIO 6L - LOGIC 6	6	65803	267	38	S/D	I/O 3:AUDIO 6L - LOGIC 6	6	65867	331	54	S/D
11	B	DSP0	6	65676	140	6	SD	DSP 2	6	65740	204	22	SD	AUDIO 6R	6	65804	268	38	S/D	AUDIO 6R	6	65868	332	54	S/D
12	C	DSP0	7	65677	141	7	SD	DSP 2	7	65741	205	23	SD	I/O 1:AUDIO 7L - LOGIC 7	7	65805	269	39	S/D	I/O 3:AUDIO 7L - LOGIC 7	7	65869	333	55	S/D
13	D	DSP0	7	65678	142	7	SD	DSP 2	7	65742	206	23	SD	AUDIO 7R	7	65806	270	39	S/D	AUDIO 7R	7	65870	334	55	S/D
14	E	DSP0	8	65679	143	8	SD	DSP 2	8	65743	207	24	SD	I/O 1:AUDIO 8L - LOGIC 8	8	65807	271	40	S/D	I/O 3:AUDIO 8L - LOGIC 8	8	65871	335	56	S/D
15	F	DSP0	8	65680	144	8	SD	DSP 2	8	65744	208	24	SD	AUDIO 8R	8	65808	272	40	S/D	AUDIO 8R	8	65872	336	56	S/D
16	10	DSP1	1	65681	145	9	SD	KSU (DSP 3)	1	65745	209	25	SD	I/O 2:AUDIO 1L - LOGIC 1	1	65809	273	41	S/D	KSU A, Lt alg - Studio 2 Mon L	1	65873	337	57	S/D
17	11	DSP1	1	65682	146	9	SD	KSU (DSP 3)	1	65746	210	25	SD	AUDIO 1R	1	65810	274	41	S/D	KSU A Rt, alg - Studio 2 Mon R	1	65874	338	57	S/D
18	12	DSP1	2	65683	147	10	SD	KSU (DSP 3)	2	65747	211	26	SD	I/O 2:AUDIO 2L - LOGIC 2	2	65811	275	42	S/D	KSU B, Lt alg - LOGIC I/O B	2	65875	339	58	S/D
19	13	DSP1	2	65684	148	10	SD	KSU (DSP 3)	2	65748	212	26	SD	AUDIO 2R	2	65812	276	42	S/D	KSU B, Right analog	2	65876	340	58	S/D
20	14	DSP1	3	65685	149	11	SD	KSU (DSP 3)	3	65749	213	27	SD	I/O 2:AUDIO 3L - LOGIC 3	3	65813	277	43	S/D	KSU C, Lt alg - LOGIC I/O C	3	65877	341	59	S/D
21	15	DSP1	3	65686	150	11	SD	KSU (DSP 3)	3	65750	214	27	SD	AUDIO 3R	3	65814	278	43	S/D	KSU C, Right analog	3	65878	342	59	S/D
22	16	DSP1	4	65687	151	12	SD	KSU (DSP 3)	4	65751	215	28	SD	I/O 2:AUDIO 4L - LOGIC 4	4	65815	279	44	S/D	KSU D, Lt alg - LOGIC I/O D	4	65879	343	60	S/D
23	17	DSP1	4	65688	152	12	SD	KSU (DSP 3)	4	65752	216	28	SD	AUDIO 4R	4	65816	280	44	S/D	KSU D, Right analog	4	65880	344	60	S/D
24	18	DSP1	5	65689	153	13	SD	KSU Phantom DSP 3	5	65753	217	29	SD	I/O 2:AUDIO 5L - LOGIC 5	5	65817	281	45	S/D	KSU A, Lt dig - Meter 2 Feed L	5	65881	345	61	S/D
25	19	DSP1	5	65690	154	13	SD	KSU Phantom DSP 3	5	65754	218	29	SD	AUDIO 5R	5	65818	282	45	S/D	KSU A, Rt dig - Meter 2 Feed R	5	65882	346	61	S/D
26	1A	DSP1	6	65691	155	14	SD	KSU Phantom DSP 3	6	65755	219	30	SD	I/O 2:AUDIO 6L - LOGIC 6	6	65819	283	46	S/D	KSU B, Lt dig - Control Rm Mon L	6	65883	347	62	S/D
27	1B	DSP1	6	65692	156	14	SD	KSU Phantom DSP 3	6	65756	220	30	SD	AUDIO 6R	6	65820	284	46	S/D	KSU B, Rt dig - Control Rm Mon R	6	65884	348	62	S/D
28	1C	DSP1	7	65693	157	15	SD	KSU Phantom DSP 3	7	65757	221	31	SD	I/O 2:AUDIO 7L - LOGIC 7	7	65821	285	47	S/D	KSU C, Lt dig - Studio 1 Mon L	7	65885	349	63	S/D
29	1D	DSP1	7	65694	158	15	SD	KSU Phantom DSP 3	7	65758	222	31	SD	AUDIO 7R	7	65822	286	47	S/D	KSU C, Rt dig - Studio 1 Mon R	7	65886	350	63	S/D
30	1E	DSP1	8	65695	159	16	SD	KSU Phantom DSP 3	8	65759	223	32	SD	I/O 2:AUDIO 8L - LOGIC 8	8	65823	287	48	S/D	KSU D, Lt dig - Synth Air Feed L	8	65887	351	64	S/D
31	1F	DSP1	8	65696	160	16	SD	KSU Phantom DSP 3	8	65760	224	32	SD	AUDIO 8R	8	65824	288	48	S/D	KSU D, Rt dig - Synth Air Feed R	8	65888	352	64	S/D
32	20	Mix-Minus 1, Left	-	65697	161		S	Program 1 left	-	65761	225		S	Program 3 left	-	65825	289		S	Program 1 mono	-	65889	353		S
33	21	Mis-Minus 1, Right	-	65698	162		S	Program 1 right	-	65762	226		S	Program 3 right	-	65826	290		S	Program 2 mono	-	65890	354		S
34	22	Mix-Minus 2, Left	-	65699	163		S	Program 2 left	-	65763	227		S	Program 4 left	-	65827	291		S	Program 3 mono	-	65891	355		S
35	23	Mix-Minus 2, Right	-	65700	164		S	Program 2 right	-	65764	228		S	Program 4 right	-	65828	292		S	Program 4 mono	-	65892	356		S
36	24	Mix-Minus 3, Left	-	65701	165		S	Util 1 left	-	65765	229		S	Util 3 left	-	65829	293		S	Off-line 1 (mics)	-	65893	357		S
37	25	Mix-Minus 3, Right	-	65702	166		S	Util 1 right	-	65766	230		S	Util 3 right	-	65830	294		S	Off-line 1 (lines)	-	65894	358		S
38	26	Mix-Minus 4, Left	-	65703	167		S	Util 2 left	-	65767	231		S	Util 4 left	-	65831	295		S	Off-line 2 (mics)	-	65895	359		S
39	27	Mix-Minus 4, Right	-	65704	168		S	Util 2 right	-	65768	232		S	Util 4 right	-	65832	296		S	Off-line 2 (lines)	-	65896	360		S
40	28	Mix-Minus 5, Left	-	65705	169		S	Send 1 left	-	65769	233		S	Send 2 left	-	65833	297		S	Telco/codec 1	-	65897	361		S
41	29	Mix-Minus 5, Right	-	65706	170		S	Send 1 right	-	65770	234		S	Send 2 right	-	65834	298		S	Telco/codec 2	-	65898	362		S
42	2A	Mix-Minus 6, Left	-	65707	171		S	Cue left	-	65771	235		S	Solo left	-	65835	299		S	Telco/codec 3	-	65899	363		S
43	2B	Mix-Minus 6, Right	-	65708	172		S	Cue right	-	65772	236		S	Solo right	-	65836	300		S	Telco/codec 4	-	65900	364		S
44	2C	Telco Record, Left	-	65709	173		S	Talk to studio 1	-	65773	237		S	Talk to studio 2	-	65837	301		S	Telco/codec 5	-	65901	365		S
45	2D	Telco Record, Right	-	65710	174		S	Talk to studio 1, host	-	65774	238		S	Talk to studio 2, host	-	65838	302		S	Telco/codec 6	-	65902	366		S
46	2E	Telco Monitor, Left	-	65711	175		S	Talk to studio 1, co-host	-	65775	239		S	Talk to studio 2, co-host	-	65839	303		S	RMX CR TALK Mic	-	65903	367		S
47	2F	Telco Monitor, Right	-	65712	176		S	Talk to control room	-	65776	240		S	Talk to external	-	65840	304		S	RMX PD TALK Mic	-	65904	368		S
48	30	unused timeslot	-	65713	177			KSU A, Left analog	-	65777	241		D	unused timeslot	-	65841	305			unused timeslot	-	65905	369		
49	31	unused timeslot	-	65714	178			KSU A, Right analog	-	65778	242		D	unused timeslot	-	65842	306			unused timeslot	-	65906	370		
50	32	unused timeslot	-	65715	179			KSU B, Left analog	-	65779	243		D	unused timeslot	-	65843	307			unused timeslot	-	65907	371		
51	33	unused timeslot	-	65716	180			KSU B, Right analog	-	65780	244		D	unused timeslot	-	65844	308			unused timeslot	-	65908	372		
52	34	unused timeslot	-	65717	181			KSU C, Left analog	-	65781	245		D	unused timeslot	-	65845	309			unused timeslot	-	65909	373		
53	35	unused timeslot	-	65718	182			KSU C, Right analog	-	65782	246		D	unused timeslot	-	65846	310			unused timeslot	-	65910	374		
54	36	unused timeslot	-	65719	183			KSU D, Left analog	-	65783	247		D	unused timeslot	-	65847	311			unused timeslot	-	65911	375		
55	37	unused timeslot	-	65720	184			KSU D, Right analog	-	65784	248		D	unused timeslot	-	65848	312			unused timeslot	-	65912	376		
56	38	unused timeslot	-	65721	185			KSU A, Left digital	-	65785	249		D	unused timeslot	-	65849	313			unused timeslot	-	65913	377		
57	39	unused timeslot	-	65722	186			KSU A, Right digital	-	65786	250		D	unused timeslot	-	65850	314			unused timeslot	-	65914	378		
58	3A	unused timeslot	-	65723	187			KSU B, Left digital	-	65787	251		D	unused timeslot	-	65851	315			unused timeslot	-	65915	379		
59	3B	unused timeslot	-	65724	188			KSU B, Right digital	-	65788	252		D	unused timeslot	-	65852	316			unused timeslot	-	65916	380		
60	3C	unused timeslot	-	65725	189			KSU C, Left digital	-	65789</															